

## APPLICATION OF THE DRAZIN INVERSE TO THE ANALYSIS OF DESCRIPTOR FRACTIONAL DISCRETE-TIME LINEAR SYSTEMS WITH REGULAR PENCILS

TADEUSZ KACZOREK

Faculty of Electrical Engineering  
Białystok Technical University, ul. Wiejska 45D, 15-351 Białystok, Poland  
e-mail: kaczorek@isep.pw.edu.pl

The Drazin inverse of matrices is applied to find the solutions of the state equations of descriptor fractional discrete-time systems with regular pencils. An equality defining the set of admissible initial conditions for given inputs is derived. The proposed method is illustrated by a numerical example.

**Keywords:** Drazin inverse, descriptor, fractional system, discrete-time system, linear system.

*Dedicated to Bogumiła Adamczyk on the occasion of her birthday*

### 1. Introduction

Descriptor (singular) linear systems were considered in many papers and books (Bru *et al.*, 2000; 2002; 2003; Campbell *et al.*, 1976; Dai, 1989; Dodig and Stosic, 2009; Fahmy and O'Reill, 1989; Kaczorek, 1992; 2004; 2007b; 2011a; 2011d; Van Dooren, 1979; Virnik, 2008). The eigenvalues and invariants assignment by state and output feedbacks were investigated by Fahmy and O'Reill (1989), Gantmacher (1960), Kaczorek (2004) as well as Kucera and Zagalak (1988), and the realization problem for singular positive continuous-time systems with delays was examined by Kaczorek (2007b). The computation of Kronecker's canonical form of the singular pencil was analyzed by Van Dooren (1979). Positive linear systems with different fractional orders were addressed by Kaczorek (2010), who also discussed selected problems of fractional linear systems theory (Kaczorek, 2011b).

A dynamical system is called positive if its trajectory starting from any nonnegative initial state remains forever in the positive orthant for all nonnegative inputs. An overview of the state of the art in positive systems theory is given by Farina and Rinaldi (2000), Commalut and Marchand (2006), as well as Kaczorek (2002; 2007a). A variety of models having positive behavior can be found

in engineering, economics, social sciences, biology and medicine, etc.

Descriptor standard positive linear systems using the Drazin inverse were addressed by Bru *et al.* (2003; 2000; 2002) and Kaczorek (2002; 2011b). The shuffle algorithm was applied to check the positivity of descriptor linear systems by Kaczorek (2011a), while the stability of positive descriptor systems was investigated by Virnik (2008). Reduction and decomposition of descriptor fractional discrete-time linear systems were considered by Kaczorek (2011d), who also introduced a new class of descriptor fractional linear discrete-time systems (Kaczorek, 2011c).

In this paper the Drazin inverse of matrices will be applied to find the solutions of the state equations of descriptor fractional discrete-time linear systems with regular pencils. The paper is organized as follows. In Section 2 the state equation of the descriptor fractional linear discrete-time system and some basic definitions of the Drazin inverse are recalled. The solution to the state equation is given in Section 3. The proposed method is illustrated by numerical examples in Section 4. Concluding remarks are given in Section 5.

The following notation will be used:  $\mathbb{R}$  is the set of real numbers,  $\mathbb{R}^{n \times m}$  is the set of  $n \times m$  real matrices and  $\mathbb{R}^n = \mathbb{R}^{n \times 1}$ ,  $\mathbb{Z}_+$  is the set of nonnegative integers,  $\mathbb{N}$  is the set of natural numbers,  $I_n$  is the  $n \times n$  identity matrix,  $\ker A$  is the kernel of the matrix,  $\mathbb{C}$  is the field of complex numbers.

## 2. Preliminaries

Consider the descriptor fractional discrete-time linear system

$$E\Delta^\alpha x_{i+1} = Ax_i + Bu_i, \quad i \in \mathbb{Z}_+, \quad 0 < \alpha < 1, \quad (1)$$

where  $\alpha$  is the fractional order,  $x_i \in \mathbb{R}^n$  is the state vector,  $u_i \in \mathbb{R}^m$  is the input vector and  $E, A \in \mathbb{R}^{n \times n}$ ,  $B \in \mathbb{R}^{n \times m}$ . It is assumed that  $\det E = 0$ , but the pencil  $(E, A)$  is regular, i.e.,

$$\det[Es - A] \neq 0 \quad \text{for some } s \in \mathbb{C}. \quad (2)$$

The fractional difference of the order  $\alpha$  is defined by (Kaczorek, 2011b)

$$\Delta^\alpha x_i = \sum_{k=0}^i c_k x_{i-k}, \quad n-1 < \alpha < n \in \mathbb{N}, \quad (3)$$

where

$$c_k = (-1)^k \binom{\alpha}{k}, \quad k = 0, 1, \dots, \quad (4a)$$

and

$$\binom{\alpha}{k} = \begin{cases} 1 & \text{for } k = 0, \\ \frac{\alpha(\alpha-1)\dots(\alpha-k+1)}{k!} & \text{for } k = 1, 2, \dots \end{cases} \quad (4b)$$

Substitution of (3) into (1) yields

$$Ex_{i+1} = Fx_i - \sum_{k=1}^i Ec_{k+1}x_{i-k} + Bu_i, \quad i \in \mathbb{Z}_+, \quad (5a)$$

where

$$F = A - Ec_1. \quad (5b)$$

Assuming that

$$\det[Ec - F] \neq 0 \quad \text{for some } c \in \mathbb{C}, \quad (6)$$

and premultiplying (5a) by  $[Ec - F]^{-1}$ , we obtain

$$\bar{E}x_{i+1} = \bar{F}x_i - \sum_{k=1}^i \bar{E}c_{k+1}x_{i-k} + \bar{B}u_i, \quad (7a)$$

where

$$\begin{aligned} \bar{E} &= [Ec - F]^{-1}E, & \bar{F} &= [Ec - F]^{-1}F, \\ \bar{B} &= [Ec - F]^{-1}B. \end{aligned} \quad (7b)$$

**Definition 1.** (Kaczorek, 1992) The smallest nonnegative integer  $q$  satisfying

$$\text{rank } \bar{E}^q = \text{rank } \bar{E}^{q+1} \quad (8)$$

is called the *index* of the matrix  $\bar{E} \in \mathbb{R}^{n \times n}$ .

**Definition 2.** (Kaczorek, 1992) A matrix  $\bar{E}^D$  is called the *Drazin inverse* of  $\bar{E} \in \mathbb{R}^{n \times n}$  if it satisfies the conditions

$$\bar{E}\bar{E}^D = \bar{E}^D\bar{E}, \quad (9a)$$

$$\bar{E}^D\bar{E}\bar{E}^D = \bar{E}^D, \quad (9b)$$

$$\bar{E}^D\bar{E}^{q+1} = \bar{E}^q, \quad (9c)$$

where  $q$  is the index of  $\bar{E}$  defined by (8).

The Drazin inverse  $\bar{E}^D$  of a square matrix  $\bar{E}$  always exists and is unique (Campbell *et al.*, 1976; Kaczorek, 1992). If  $\det \bar{E} \neq 0$  then  $\bar{E}^D = \bar{E}^{-1}$ . Some methods for computation of the Drazin inverse are given by Kaczorek (1992).

**Lemma 1.** (Campbell *et al.*, 1976; Kaczorek, 1992) *The matrices  $\bar{E}$  and  $\bar{F}$  defined by (7b) satisfy the following equalities:*

$$\begin{aligned} \bar{F}\bar{E} &= \bar{E}\bar{F}, & \bar{F}^D\bar{E} &= \bar{E}\bar{F}^D, \\ \bar{E}^D\bar{F} &= \bar{F}\bar{E}^D, & \bar{F}^D\bar{E}^D &= \bar{E}^D\bar{F}^D, \end{aligned} \quad (10a)$$

$$\ker \bar{F}_1 \cap \ker \bar{E} = \{0\}, \quad (10b)$$

$$\begin{aligned} \bar{E} &= T \begin{bmatrix} J & 0 \\ 0 & N \end{bmatrix} T^{-1}, \\ \bar{F} &= T \begin{bmatrix} A_1 & 0 \\ 0 & A_2 \end{bmatrix} T^{-1}, \\ \bar{E}^D &= T \begin{bmatrix} J^{-1} & 0 \\ 0 & 0 \end{bmatrix} T^{-1}, \end{aligned} \quad (10c)$$

$$\begin{aligned} \det T &\neq 0, \quad J \in \mathbb{R}^{n_1 \times n_1} \text{ is nonsingular,} \\ N &\in \mathbb{R}^{n_2 \times n_2} \text{ is nilpotent,} \quad A_1 \in \mathbb{R}^{n_1 \times n_1}, \\ A_2 &\in \mathbb{R}^{n_2 \times n_2}, \quad n_1 + n_2 = n, \end{aligned}$$

$$\begin{aligned} (I_n - \bar{E}\bar{E}^D)\bar{F}\bar{F}^D &= I_n - \bar{E}\bar{E}^D \\ \text{and } (I_n - \bar{E}\bar{E}^D)(\bar{E}\bar{F}^D)^q &= 0. \end{aligned} \quad (10d)$$

## 3. Solution to the state equation

In this section the solution to the state equation (1) will be presented by the use of the Drazin inverses of the matrices  $\bar{E}$  and  $\bar{F}$ .

**Theorem 1.** *The solution to Eqn. (7a) with an admissible initial condition  $x_0$  is given by*

$$\begin{aligned} x_i &= (\bar{E}^D\bar{F})^i \bar{E}^D \bar{E}x_0 \\ &+ \sum_{k=0}^{i-1} \bar{E}^D (\bar{E}^D\bar{F})^{i-k-1} \left[ \bar{B}u_k - \sum_{j=1}^k \bar{E}c_{j+1}x_{k-j} \right] \\ &+ (\bar{E}\bar{E}^D - I_n) \sum_{k=0}^{q-1} (\bar{E}\bar{F}^D)^k \bar{F}^D \bar{B}u_{i+k}, \end{aligned} \quad (11)$$

where  $q$  is the index of  $\bar{E}$ .

*Proof.* Using (11) and taking into account (9) and (10), we obtain

$$\begin{aligned} \bar{E}x_{i+1} &= \bar{E}(\bar{E}^D \bar{F})^{i+1} \bar{E}^D \bar{E}x_0 \\ &+ \sum_{k=0}^i \bar{E} \bar{E}^D (\bar{E}^D \bar{F})^{i-k} \left[ \bar{B}u_k - \sum_{j=1}^k \bar{E}c_{j+1}x_{k-j+1} \right] \\ &+ \bar{E}(\bar{E} \bar{E}^D - I_n) \sum_{k=0}^{q-1} (\bar{E} \bar{F}^D)^k \bar{F}^D \bar{B}u_{i+k+1} \\ &= \bar{F}(\bar{E}^D \bar{F})^i \bar{E}^D \bar{E}x_0 \\ &+ \sum_{k=0}^{i-1} (\bar{E}^D \bar{F})^{i-k} \left[ \bar{B}u_k - \sum_{j=1}^k \bar{E}c_{j+1}x_{k-j} \right] + \bar{B}u_i \\ &+ (I_n - \bar{E} \bar{E}^D) \sum_{k=0}^{q-1} (-\bar{F}^D \bar{E})^k \bar{F} \bar{F}^D \bar{B}u_{i+k} \end{aligned} \tag{12}$$

and

$$\begin{aligned} \bar{F}x_i &= \bar{F}(\bar{E}^D \bar{F})^i \bar{E}^D \bar{E}x_0 \\ &+ \sum_{k=0}^{i-1} \bar{F} \bar{E}^D (\bar{E}^D \bar{F})^{i-k-1} \left[ \bar{B}u_k - \sum_{j=1}^k \bar{E}c_{j+1}x_{k-j} \right] \\ &+ \bar{F}(\bar{E} \bar{E}^D - I_n) \sum_{k=0}^{q-1} (\bar{E} \bar{F}^D)^k \bar{F}^D \bar{B}u_{i+k}. \end{aligned} \tag{13}$$

Hence

$$\bar{E}x_{i+1} - \bar{F}x_i - \sum_{k=1}^j \bar{E}c_{k+1}x_{i-k} = \bar{B}u_i. \tag{14}$$

Thus, the solution (11) satisfies Eqn. (7a). ■

From (11), for  $i = 0$  we have

$$x_0 = \bar{E}^D \bar{E}x_0 + (\bar{E} \bar{E}^D - I_n) \sum_{k=0}^{q-1} (\bar{E} \bar{F}^D)^k \bar{F}^D \bar{B}u_k. \tag{15}$$

The set of admissible initial conditions  $x_0$  for given input  $u_i$  is given by (15). In a practical case, for  $u_i = 0, i \in \mathbb{Z}_+$  we have  $x_0 = \bar{E}^D \bar{E}x_0$ . Thus, the equation  $\bar{E}x_{i+1} = Ax_i$  has a unique solution if and only if  $x_0 \in \text{Im} \bar{E} \bar{E}^D$ , where ‘Im’ denotes the image.

### 4. Example

Find the solution  $x_i$  to Eqn. (1) with  $\alpha = 0.5$  and the matrices

$$E = \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix}, \quad A = \begin{bmatrix} 0 & 0 \\ 1 & -2 \end{bmatrix}, \quad B = \begin{bmatrix} 1 \\ 2 \end{bmatrix}, \tag{16}$$

and admissible initial conditions for given input  $u_i, i \in \mathbb{Z}_+$ . The pencil of (16) is regular since

$$\begin{aligned} \det[Ez - A] &= \begin{vmatrix} z & 0 \\ -1 & 2 \end{vmatrix} = 2z, \\ F = A - Ec_1 &= A + E\alpha = \begin{bmatrix} \alpha & 0 \\ 1 & -2 \end{bmatrix}, \\ q &= 1. \end{aligned} \tag{17}$$

For  $c = 1$  the matrices (7b) have the forms

$$\begin{aligned} \bar{E} &= [Ec - F]^{-1} E = \begin{bmatrix} 1 - \alpha & 0 \\ -1 & 2 \end{bmatrix}^{-1} \begin{bmatrix} 1 & 0 \\ 0 & 0 \end{bmatrix} \\ &= \frac{1}{2(1 - \alpha)} \begin{bmatrix} 2 & 0 \\ 1 & 0 \end{bmatrix} = \begin{bmatrix} 2 & 0 \\ 1 & 0 \end{bmatrix}, \\ \bar{F} &= [Ec - F]^{-1} F = \begin{bmatrix} 1 - \alpha & 0 \\ -1 & 2 \end{bmatrix}^{-1} \begin{bmatrix} \alpha & 0 \\ 1 & -2 \end{bmatrix} \\ &= \frac{1}{2(1 - \alpha)} \begin{bmatrix} 2\alpha & 0 \\ 1 & -2(1 + \alpha) \end{bmatrix} = \begin{bmatrix} -1 & 0 \\ 1 & -1 \end{bmatrix}, \\ \bar{B} &= [Ec - F]^{-1} B = \begin{bmatrix} 1 - \alpha & 0 \\ -1 & 2 \end{bmatrix}^{-1} \begin{bmatrix} 1 \\ 2 \end{bmatrix} \\ &= \frac{1}{2(1 - \alpha)} \begin{bmatrix} 2 \\ 3 - 2\alpha \end{bmatrix} = \begin{bmatrix} 2 \\ 2 \end{bmatrix}. \end{aligned} \tag{18}$$

Using (10c) and (18), we obtain

$$\bar{E} = T^{-1} \begin{bmatrix} 2 & 0 \\ 0 & 0 \end{bmatrix} T, \quad T = \begin{bmatrix} 1 & 0 \\ 1/2 & 1 \end{bmatrix} \tag{19}$$

and

$$\bar{E}^D = T^{-1} \begin{bmatrix} 1/2 & 0 \\ 0 & 0 \end{bmatrix} T = \begin{bmatrix} 1/2 & 0 \\ -1/4 & 0 \end{bmatrix}. \tag{20}$$

Note that

$$\det \bar{F} = \begin{vmatrix} 1 & 0 \\ 1 & -1 \end{vmatrix} = -1 \neq 0 \tag{21}$$

and

$$\bar{F}^D = \bar{F}^{-1} = \begin{bmatrix} 1 & 0 \\ 1 & -1 \end{bmatrix}. \tag{22}$$

Taking into account that

$$\begin{aligned} \bar{E}^D \bar{F} &= \begin{bmatrix} 1/2 & 0 \\ -1/4 & 0 \end{bmatrix} \begin{bmatrix} 1 & 0 \\ 1 & -1 \end{bmatrix} = \begin{bmatrix} 1/2 & 0 \\ -1/4 & 0 \end{bmatrix}, \\ \bar{E} \bar{E}^D &= \begin{bmatrix} 2 & 0 \\ 1 & 0 \end{bmatrix} \begin{bmatrix} 1/2 & 0 \\ -1/4 & 0 \end{bmatrix} = \begin{bmatrix} 1 & 0 \\ 1/2 & 0 \end{bmatrix} \end{aligned} \tag{23}$$

and using (11), we obtain

$$\begin{aligned}
 x_i = & \begin{bmatrix} 1/2 & 0 \\ -1/4 & 0 \end{bmatrix}^i \begin{bmatrix} 1 & 0 \\ -1/2 & 0 \end{bmatrix} x_0 \\
 & + \sum_{k=0}^{i-1} \begin{bmatrix} 1/2 & 0 \\ -1/4 & 0 \end{bmatrix} \begin{bmatrix} 1/2 & 0 \\ -1/4 & 0 \end{bmatrix}^{i-k-1} \\
 & \times \left\{ \begin{bmatrix} 2 \\ 2 \end{bmatrix} u_k - \sum_{j=1}^k \begin{bmatrix} 2 & 0 \\ 1 & 0 \end{bmatrix} c_{j+1} x_{k-j} \right\} \\
 & + \begin{bmatrix} 0 & 0 \\ 1/2 & -1 \end{bmatrix} \begin{bmatrix} 1 \\ -1 \end{bmatrix} u_i,
 \end{aligned} \quad (24)$$

where the coefficients  $c_j$  are defined by (4a) for  $\alpha = 0.5$ .

From (24), for  $i = 0$  we have

$$x_0 = \begin{bmatrix} 1 & 0 \\ 1/2 & 0 \end{bmatrix} x_0 + \begin{bmatrix} 0 \\ -2 \end{bmatrix} u_0. \quad (25)$$

Hence, for given  $u_0$ , the admissible initial condition  $x_0$  should satisfy (25).

## 5. Concluding remarks

The Drazin inverse of matrices has been applied to find the solutions of the state equations of the descriptor fractional discrete-time systems with regular pencils. The equality (15) defining the set of admissible initial conditions for given inputs has been derived. The proposed method has been illustrated by a numerical example.

Comparing the presented method with that based on the Weierstrass decomposition of the regular pencil (Kaczorek, 2011c), we may conclude that the proposed approach is computationally attractive since the Drazin inverse of matrices can be computed by the use of well-known numerical methods (Kaczorek, 1992). The presented method can be extended to descriptor fractional continuous-time linear systems. An open problem is the extension of the deliberations to standard and positive continuous-discrete descriptor fractional linear systems.

## Acknowledgment

This work was supported by the National Science Centre in Poland under the grant no. N N514 6389 40.

## References

- Bru, R., Coll, C., Romero-Vivo S. and Sanchez, E. (2003). Some problems about structural properties of positive descriptor systems, in L. Benvenuti, A. Santis and L. Farina (Eds.), *Positive Systems*, Lecture Notes in Control and Information Sciences, Vol. 294, Springer, Berlin, pp. 233–240.
- Bru, R., Coll, C. and Sanchez, E. (2000). About positively discrete-time singular systems, in N.E. Mastorakis (Ed.) *System and Control: Theory and Applications*, Electrical and Computer Engineering Series, World Scientific and Engineering Society, Athens, pp. 44–48.
- Bru, R., Coll, C. and Sanchez, E. (2002). Structural properties of positive linear time-invariant difference-algebraic equations, *Linear Algebra and Applications* **349**(1–3): 1–10.
- Campbell, S.L., Meyer, C.D. and Rose, N.J. (1976). Applications of the Drazin inverse to linear systems of differential equations with singular constant coefficients, *SIAM Journal on Applied Mathematics* **31**(3): 411–425.
- Commalut, C. and Marchand, N. (2006). *Positive Systems*, Lecture Notes in Control and Information Sciences, Vol. 341, Springer-Verlag, Berlin.
- Dai, L. (1989). *Singular Control Systems*, Lectures Notes in Control and Information Sciences, Vol. 118, Springer-Verlag, Berlin.
- Dodig, M. and Stosic, M. (2009). Singular systems state feedbacks problems, *Linear Algebra and Its Applications* **431**(8): 1267–1292.
- Fahmy, M.H. and O'Reill, J. (1989). Matrix pencil of closed-loop descriptor systems: Infinite-eigenvalues assignment, *International Journal of Control* **49**(4): 1421–1431.
- Farina, L. and Rinaldi, S. (2000). *Positive Linear Systems*, J. Wiley, New York, NY.
- Gantmacher, F.R. (1960). *The Theory of Matrices*, Chelsea Publishing Co., New York, NY.
- Kaczorek, T. (1992). *Linear Control Systems*, Vol. 1, Research Studies Press, J. Wiley, New York, NY.
- Kaczorek, T. (2002). *Positive 1D and 2D Systems*, Springer-Verlag, London.
- Kaczorek, T. (2004). Infinite eigenvalue assignment by an output/feedback for singular systems, *International Journal of Applied Mathematics and Computer Science* **14**(1): 19–23.
- Kaczorek, T. (2007a). *Polynomial and Rational Matrices. Applications in Dynamical Systems Theory*, Springer-Verlag, London.
- Kaczorek, T. (2007b). Realization problem for singular positive continuous-time systems with delays, *Control and Cybernetics* **36**(1): 47–57.
- Kaczorek, T. (2010). Positive linear systems with different fractional orders, *Bulletin of the Polish Academy of Sciences: Technical Sciences* **58**(3): 453–458.
- Kaczorek, T. (2011a). Checking of the positivity of descriptor linear systems by the use of the shuffle algorithm, *Archives of Control Sciences* **21**(3): 287–298.
- Kaczorek, T. (2011b). *Selected Problems of Fractional Systems Theory*, Springer-Verlag, Berlin.
- Kaczorek T. (2011c). Singular fractional discrete-time linear systems, *Control and Cybernetics* **40**(3): 1–8.
- Kaczorek T. (2011d). Reduction and decomposition of singular fractional discrete-time linear systems, *Acta Mechanica et Automatica* **5**(4): 1–5.
- Kucera, V. and Zagalak, P. (1988). Fundamental theorem of state feedback for singular systems, *Automatica* **24**(5): 653–658.

Van Dooren, P. (1979). The computation of Kronecker's canonical form of a singular pencil, *Linear Algebra and Its Applications* **27**: 103–140.

Virnik, E. (2008). Stability analysis of positive descriptor systems, *Linear Algebra and Its Applications* **429**(10): 2640–2659.



**Tadeusz Kaczorek** received the M.Sc., Ph.D. and D.Sc. degrees in electrical engineering from the Warsaw University of Technology in 1956, 1962 and 1964, respectively. In the years 1968–69 he was the dean of the Electrical Engineering Faculty, and in the period of 1970–73 he was a deputy rector of the Warsaw University of Technology. In 1971 he became a professor and in 1974 a full professor at the same university. Since 2003 he has been a professor at Białystok

Technical University. In 1986 he was elected a corresponding member and in 1996 a full member of the Polish Academy of Sciences. In the years 1988–1991 he was the director of the Research Centre of the Polish Academy of Sciences in Rome. In 2004 he was elected an honorary member of the Hungarian Academy of Sciences. He has been granted honorary doctorates by nine universities. His research interests cover systems theory, especially singular multidimensional systems, positive multidimensional systems, singular positive 1D and 2D systems, as well as positive fractional 1D and 2D systems. He initiated research in the field of singular 2D, positive 2D and positive fractional linear systems. He has published 24 books (six in English) and over 1000 scientific papers. He has also supervised 69 Ph.D. theses. He is the editor-in-chief of the *Bulletin of the Polish Academy of Sciences: Technical Sciences* and a member of editorial boards of ten international journals.

Received: 25 April 2012

Revised: 24 October 2012

Duan Guang-Ren: Analysis and Design of Descriptor Linear Systems. Springer, New York, 2010. Language: n/d. confirm. report. A T. Kaczorek: Application of Drazin inverse to analysis of descriptor fractional discrete-time linear systems with regular pencils. Int. J. Appl. Math. Comput. Sci., 23(1), (2013), 29-34. [http://gateway.webofknowledge.com/gateway/Gateway.cgi?GWVersion=2&SrcApp=PARTNER\\_APP&SrcAuth=LinksAMR&KeyUT=WOS:000317725800003&DestLinkType=FullRecord&DestApp=ALL\\_WOS&UsrCustomerID=b7bc2757938ac7a7a821505f8243d9f3](http://gateway.webofknowledge.com/gateway/Gateway.cgi?GWVersion=2&SrcApp=PARTNER_APP&SrcAuth=LinksAMR&KeyUT=WOS:000317725800003&DestLinkType=FullRecord&DestApp=ALL_WOS&UsrCustomerID=b7bc2757938ac7a7a821505f8243d9f3)

Journal. Language: n/d. In mathematics, the discrete Fourier transform (DFT) converts a finite sequence of equally-spaced samples of a function into a same-length sequence of equally-spaced samples of the discrete-time Fourier transform (DTFT), which is a complex-valued function of frequency. The interval at which the DTFT is sampled is the reciprocal of the duration of the input sequence. An inverse DFT is a Fourier series, using the DTFT samples as coefficients of complex sinusoids at the corresponding DTFT frequencies. It... Application of the Drazin inverse to the analysis of descriptor fractional discrete-time linear systems with regular pencils. Tadeusz Kaczorek. Full text PDF. Abstract The Drazin inverse of matrices is applied to find the solutions of the state equations of descriptor fractional discrete-time systems with regular pencils. An equality defining the set of admissible initial conditions for given inputs is derived. The proposed method is illustrated by a numerical example. Keywords Drazin inverse, descriptor, fractional system, discrete-time system, linear system. DOI 10.2478/amcs-2013-0003. BACK. Decentralized Stabilization of Fractional Positive Descriptor Discrete-Time Linear Systems. Non-invasive Control of the Fractional Hegselmann-Krause Type Model. Differintegarator Based on Fractional Calculus of Convex Functions. The AQM Dropping Packet Probability Function Based on Non-integer Order PID Controller. New Numerical Techniques for Solving Fractional Partial Differential Equations in Conformable Sense. Implementation of Low-Pass Fractional Filtering for the Purpose of Analysis of Electroencephalographic Signals. 5. Campbell, S.L., Meyer, C.D., Rose, N.J.: Applications of the Drazin inverse to linear systems of differential equations with singular constructions. SIAMJ Appl. Math. Descriptor linear systems with regular pencils have been considered in many papers and books [4-12, 15-18]. The descriptor linear systems with singular pencils has been addressed in [10, 11]. The Drazin inverse of matrix to analysis of linear algebraic-differential equations has been applied in [4-7, 9, 11]. The positive descriptor linear systems with regular pencils have been analyzed in [1-3, 18]. In this paper a new method of analysis of descriptor fractional continuous-time linear systems with singular pencils will be proposed. The method is based on transformation of singular pencils by the use of the shuffle algorithm. The paper is organized as follows.